


Z0805C182DSMST

Aliases (Z0805C182DSMST)

Obsolete

 ${\sf EMI \, Suppression, \, KEMET, \, Z\text{-}SMS, \, SMD \, Chip, \, Noise \, Suppression}$



| Click here for the | ne 3D model. |
|--------------------|--------------|

| General Information | |
|---------------------|--|
| Series | Z-SMS |
| Style | SMD Chip |
| Description | Chip Bead Signal Line |
| Features | Intended For Noise Suppression Around 200MHz, Effectively Increase Attenuation |
| RoHS | Yes |

| Dimensions | |
|------------|-----------------|
| L | 2mm -3mm |
| W | 1.25mm +/-0.2mm |
| Т | 0.85mm +/-0.2mm |
| В | 0.5mm +/-0.3mm |
| В | , |

| Packaging Specifications | |
|--------------------------|------|
| Packaging | T&R |
| Packaging Quantity | 2000 |

| Specifications | |
|---------------------|---------------------|
| Impedance | 1800 Ohms (100 MHz) |
| Impedance Tolerance | 25% |
| Ripple Current | 300 mA (MAX) |
| Temperature Range | -55/+125°C |
| DC Resistance | 0.45 Ohms |

Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.

Generated 08/04/2025 © 2006 - 2025 YAGEO