

## C0402C101F1GACTU

Aliases (C0402C101F1GAC7867) SMD Comm COG, Ceramic, 100 pF, 1%, 100 VDC, COG, SMD, MLCC, Ultra-Stable, Low Loss, Class I, 0402, 0.3 mm



General Information		
Series	SMD Comm COG	
Style	SMD Chip	
Description	SMD, MLCC, Ultra-Stable, Low Loss, Class I	
Features	Ultra-Stable, Low Loss, Class I	
RoHS	Yes	
Termination	Tin	
Marking	No	
AEC-Q200	No	
Typical Component Weight	1.06 mg	
Shelf Life	78 Weeks	
MSL	1	

100 pF

Dimensions	
Chip Size	0402
L	1mm +/-0.05mm
W	0.5mm +/-0.05mm
Т	0.5mm +/-0.05mm
S	0.3mm MIN
В	0.3mm +/-0.1mm

	1mm +/-0.05mm	Measurement Condition	1 MHz 1.0Vrms
	0.5mm +/-0.05mm	Tolerance	1%
	0.5mm +/-0.05mm	Voltage DC	100 VDC
	0.3mm MIN	Dielectric Withstanding Voltage	250 VDC
	0.3mm +/-0.1mm	Temperature Range	-55/+125°C
		Temp. Coefficient	COG
T&R, 180mm, Paper Tape		Capacitance Change with Reference to +25°C and 0 VDC Applied (TCC)	30 ppm/C, 1MegaHz 1.0Vrms
10000		Dissipation Factor	0.1% 1 MHz 1.0Vrms
		Aging Rate	0% Loss / Decade Hour

**Specifications** 

Capacitance

S	0.3mm MIN	Dielectric Withstanding Voltage	250 VDC
В	0.3mm +/-0.1mm	Temperature Range	-55/+125°C
		Temp. Coefficient	COG
Packaging Specifications		Capacitance Change with	30 ppm/C, 1MegaHz 1.0Vrms
Packaging	T&R, 180mm, Paper Tape	Reference to +25°C and 0 VDC Applied (TCC)	3.
Packaging Quantity	aging Quantity 10000	Discipation Factor	O 10/ 1 MI I= 1 O) /
		Dissipation Factor	0.1% 1 MHz 1.0Vrms
		Aging Rate	0% Loss/Decade Hour
		Insulation Resistance	100 GOhms

Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.

Generated 09/01/2025 © 2006 - 2025 YAGEO