


## **Z0805C121BSMST**

Aliases (Z0805C121BSMST)

## Obsolete

KEMET, Z-SMS, Ferrite Beads, Noise Suppression, 150 mOhms



Click here for the 3D model.

Dimensions	
Chip Size	0805
L	2mm -3mm
W	1.25mm +/-0.2mm
Т	0.85mm +/-0.2mm
В	0.5mm +/-0.3mm

Packaging Specifications		
Packaging	T&R	
Packaging Quantity	4000	

General Information		
Series	Z-SMS	
Style	SMD Chip	
Description	Chip Bead Signal Line	
Features	Increases The Z Characteristics Sharply Above 20MHz And Is Applicable For Radiated Noise In The 100MHz-300MHz Range, Especially Effective On Video Signals	
RoHS	Yes	
Notes	Suggested Replacement - https://productfinder.pulseelectronics.com/part/BBBK00201209121Y00.	

Specifications	
Impedance	120 Ohms (100 MHz)
Impedance Tolerance	25%
Ripple Current	800 mA (MAX)
Temperature Range	-55/+125°C
DC Resistance	0.15 Ohms

Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.