


Z0805C252DSMST

Aliases (Z0805C252DSMST)

Obsolete

KEMET, Z-SMS, Ferrite Beads, Noise Suppression, 750 mOhms



Click here for the 3D model.

Dimensions	
Chip Size	0805
L	2mm -3mm
W	1.25mm +/-0.2mm
Т	0.85mm +/-0.2mm
В	0.5mm +/-0.3mm

Packaging Specifications		
Packaging	T&R	
Packaging Quantity	2000	

General Information		
Series	Z-SMS	
Style	SMD Chip	
Description	Chip Bead Signal Line	
Features	Intended For Noise Suppression Around 200MHz, Effectively Increase Attenuation	
RoHS	Yes	
Notes	Suggested Replacement - https://www.chilisin.com/en-global/Inductor/Product/BBBK_201209/BBBK00201209252Y00.	

Specifications	
Impedance	2500 Ohms (100 MHz)
Impedance Tolerance	25%
Ripple Current	200 mA (MAX)
Temperature Range	-55/+125°C
DC Resistance	0.75 Ohms

Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.