


T541X156M063BH6710

T541 HRA, Tantalum, Polymer Tantalum, HRA Multi-Anode, 15 uF, 20%, 63 VDC, SMD, Polymer, Molded, High Reliability, Multi-Anode, Low ESR, B (0.1%/1000 Hrs), 50 mOhms, 4.3 mm, 1.3 mm, 2817 / 7343



General Information		
Series	T541 HRA	
Dielectric	Polymer Tantalum	
Style	SMD Chip	
Description	SMD, Polymer, Molded, High Reliability, Multi-Anode, Low ESR	
Features	Non-Combustible, Multiple Anode, Low ESR, High Reliability	
RoHS	No	
Prop 65	WARNING: Cancer and reproductive harm - https://www.p65warnings.ca.gov / .	
SCIP Number	b064b03e-bd75-42af-b342-1fe9 4dec2340	
Termination	Tin Lead (SnPb)	
AEC-Q200	No	
Typical Component Weight	410.89 mg	
Shelf Life	52 Weeks	
MSL	3	

15 uF

20%

63 VDC (105C), 42.21 VDC

Dimensions		
L	7.3mm +/-0.3mm	
W	4.3mm +/-0.3mm	
Н	4mm +/-0.3mm	
Т	0.13mm REF	
S	1.3mm +/-0.3mm	
F	2.4mm +/-0.1mm	
A	3.8mm MIN	
В	0.5mm +/-0.15mm	
Е	3.5mm REF	
G	3.5mm REF	
P	1.7mm REF	
R	1mm REF	
Х	0.1mm +/-0.1mm REF	

500

Packaging Quantity

Т	0.13mm REF	_	(125C)
		Temperature Range	-55/+125°C
S	1.3mm +/-0.3mm	Rated Temperature	105°C
F	2.4mm +/-0.1mm	·	
A	3.8mm MIN	Life	2000 Hrs (125C)
В	0.5mm +/-0.15mm	Humidity	60C, 90% RH, 500 Hours, rated voltage
E	3.5mm REF	Dissipation Factor	10% 120Hz 25C
G	3.5mm REF	Failure Rate	B (0.1%/1000 Hrs)
Р	1.7mm REF	ESR	50 mOhms (100kHz 25C)
R	1mm REF	Ripple Current	2324 mA (rms, 100kHz 45C)
X	0.1mm +/-0.1mm REF	Leakage Current	95 uA (5min 25°C)
Packaging Specifications	T0D 170	Testing and Reliability	10 Cycles Surge Current Testing At -55C +0C/-5C And +85C +/-5C After Voltage Aging
Packaging	T&R, 178mm		

Specifications Capacitance

Tolerance

Voltage DC

Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.

Generated 11/04/2025 © 2006 - 2025 YAGEO