


## **Z0603C331BPWZT**

Aliases (Z0603C331BPWZT)

Obsolete • Scheduled EOL - Last date to buy 30 JUN 2023

KEMET, Z-PWZ, Ferrite Beads, Noise Suppression, 130 mOhms



Click here for the 3D model.

Dimensions	
Chip Size	0603
L	1.6mm +/-0.1mm
W	0.8mm +/-0.1mm
Т	0.8mm +/-0.1mm
В	0.3mm +/-0.15mm

Packaging Specifications	
Packaging	T&R
Packaging Quantity	4000

General Information		
Series	Z-PWZ	
Style	SMD Chip	
Description	Chip Bead, Power Line	
Features	For MHz Range Applications	
RoHS	Yes	
Notes	Last Order Date June 30, 2023. Suggested Replacement - https://productfinder.pulseelectronics.com/part/BBPY00160808331Y00.	

Specifications	
Impedance	330 Ohms (100 MHz)
Impedance Tolerance	25%
Ripple Current	900 mA (MAX)
Temperature Range	-40/+125°C
DC Resistance	0.13 Ohms

Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.